

# Manual Call Point FD3050



The Manual Call Point FD3050 is designed to release a signal for a fire condition to the Fire Control Panel upon manual activation by breaking the glass on the place signed with arrows. The light indication for activating the manual call point is provided by a red LED. There is a possibility for testing by a special key.

It satisfies the requirements of the European Standard EN54-11 for a type A manual call point.

## Technical data

### Electrical installation:

– Through terminal for connecting wires with cross-section (0,8 - 1,5) mm<sup>2</sup>

### Supply voltage:

– (10-30) VDC

### Degree of protection:

– IP 40

Operational temperature range: -10oC to +55oC

Relative Humidity: (93±3)% at 40oC

Dimensions: 90x90x44 mm

Weight of the manual call point: 0,200 kg

Material: ABS, red



Office building UniPOS,  
1 Efr. Nikola Paskalev Str., Mladost 1, Sofia 1748, Bulgaria  
Phone: +359 2 97 439 25, +359 2 97 444 69

47 San Stefano Str., Pleven 5800, Bulgaria  
Phone: +359 64 891 100

**[www.unipos-bg.com](http://www.unipos-bg.com)**